Lighting System Description

Lighting room location：rear of 1st stall

The lighting console(fixed):
MA2 Full Size
Signal:DMX512

The lighting console(moved):
GrandMA2 ultra-light
Signal: DMX512

Dimmer system:
HDL/D96PLUS
Volt: 220v
Load: 16A/circle
Plug type: 16A CEE
Number of dimmer circle: 960
Signal type: DMX512
Location of DMX512 input: Lighting room
House dimmer universe: 2

Non-dim:
Volt: 220v
Load: 32A/circle
Plug type: 32A CEE
Number of non-dim circle: 124

Power distribution

Load	Volt	Connector	Number	Notes
500A	380V/50Hz	10mm lug connector	2	
100A	380V/50Hz	125A 3 phase CEE / bare end	6	
50A	380V/50Hz	63A 3 phase CEE / 32A 3 phase CEE / bare end	18	

SAIC · Shanghai Culture Square
Stage Department
July. 2018